

## (12) INTERNATIONAL APPLICATION PUBLISHED UNDER THE PATENT COOPERATION TREATY (PCT)

(19) World Intellectual Property  
Organization  
International Bureau



(43) International Publication Date  
22 January 2004 (22.01.2004)

PCT

(10) International Publication Number  
**WO 2004/008602 A1**

(51) International Patent Classification<sup>7</sup>: **H02J 7/00**,  
H02P 7/628, B60L 11/00

[JP/JP]; c/o TOYOTA JIDOSHA KABUSHIKI KAISHA,  
1, Toyota-cho, Toyota-shi, Aichi 471-8571 (JP).

(21) International Application Number:  
PCT/JP2003/008363

(74) Agents: **YOSHIDA, Kenji** et al.; 34-12, Kichijoji-honcho  
1-chome, Musashino-shi, Tokyo 180-0004 (JP).

(22) International Filing Date: 1 July 2003 (01.07.2003)

(81) Designated States (*national*): CN, US.

(25) Filing Language: English

(26) Publication Language: English

(84) Designated States (*regional*): European patent (AT, BE,  
BG, CH, CY, CZ, DE, DK, EE, ES, FI, FR, GB, GR, HU,  
IE, IT, LU, MC, NL, PT, RO, SE, SI, SK, TR).

(30) Priority Data:  
2002-204088 12 July 2002 (12.07.2002) JP  
2002-204104 12 July 2002 (12.07.2002) JP  
2002-222895 31 July 2002 (31.07.2002) JP

**Published:**

- with international search report
- before the expiration of the time limit for amending the  
claims and to be republished in the event of receipt of  
amendments


(71) Applicant (*for all designated States except US*): **TOY-  
OTA JIDOSHA KABUSHIKI KAISHA** [JP/JP]; 1, Toy-  
ota-cho, Toyota-shi, Aichi 471-8571 (JP).

(72) Inventor; and

(75) Inventor/Applicant (*for US only*): **KUSAKA, Yasushi**

*For two-letter codes and other abbreviations, refer to the "Guid-  
ance Notes on Codes and Abbreviations" appearing at the begin-  
ning of each regular issue of the PCT Gazette.*

(54) Title: METHOD AND SYSTEM FOR DETECTING THE DISCONNECTION OF AN AUXILIARY POWER SUPPLY  
FROM A POLY-PHASE MOTOR



(57) Abstract: To a neutral point of a motor (14) is connected a positive electrode of an auxiliary battery (18) and an auxiliary load (20). Voltage on a power supply line to the auxiliary load (20), a neutral point voltage, is detected, and disconnection of the auxiliary battery (18) is determined when an increase of ripples in the neutral point voltage is detected. When a voltmeter cannot be used, control of the neutral point voltage is continued by measuring current of the auxiliary battery and performing control such that the current value becomes 0. A control circuit generates, in accordance with the detected rotor angle, a voltage control signal for each phase current having the same amplitude as the carrier amplitude during startup, and compares the voltage control signal to carrier to obtain a gate signal having the same frequency as the carrier frequency. A large neutral point current is prevented.

**DESCRIPTION**

METHOD AND SYSTEM FOR DETECTING THE DISCONNECTION OF AN AUXILIARY POWER SUPPLY  
FROM A POLY-PHASE MOTOR

5

**TECHNICAL FIELD**

The present invention relates to an inverter system for driving a poly-phase motor comprising an alternating current motor which is driven by an inverter and generates electrical power and a power supply which is connected to a neutral point of the alternating current motor.

**BACKGROUND ART**

Conventionally, alternating current motors have been commonly used as a power source for various devices. In electric vehicles and hybrid vehicles, a system is typically adopted in which direct current supplied from a battery is converted into a desired alternating current by an inverter, and is then supplied to a motor. This system allows a wide range of output torques and also achieves an advantage that electrical power generated by regenerative braking can be utilized for battery charging.

Because a high voltage power supply is effective for a high power motor, electric vehicles and hybrid vehicles usually adopt a high voltage power supply on the order of several hundred volts for the main battery connected on the input side of the inverter. On the other hand, a voltage which is a half

the input voltage of the inverter is typically obtained at a neutral point of a star connection motor coil. Therefore, when a battery is connected to the neutral point, two types of direct current voltages can be obtained from the system.

5 Further, by applying chopper control to the motor coil, transfer of electrical power between two batteries can be controlled.

Accordingly, when a motor also acts as a generator in hybrid vehicles or the like, a system can be adopted in which  
10 generated electrical power is utilized for charging two batteries, thereby obtaining two power supply voltages. In particular, a capacitor can be used in place of a battery. Such a system is described, for example, in Japanese Patent Laid-Open Publication No. Hei 11-178114.

15 A variety of electrical equipment is installed on most vehicles, and an auxiliary battery of approximately 12V (14V when charged) is typically provided to power this equipment. Because the above-described neutral point voltage of the motor is about one half the voltage on the input side of the  
20 inverter, the neutral point voltage is significantly high in typical electric vehicles and hybrid vehicles, which makes it difficult to connect an auxiliary battery to the neutral point in these vehicles. Accordingly, a separate DCDC converter is provided for charging the auxiliary battery.

25 On the other hand, a so-called "dual power supply system" in which a 36-volt power supply and a 12-volt power supply are provided has been studied as a practical application example of

the above system. In this dual power supply system, because it is sufficient to set the inverter input voltage to approximately 42V when charging the 36-volt power supply and set the neutral point voltage to approximately 14V when  
5 charging the 12-volt power supply, transfer of electrical power between the two power supplies can be performed using a motor coil.

Accordingly, in the above poly-phase motor driving inverter system, electrical charges can be transferred between  
10 a high voltage side battery and a low voltage side battery using a motor coil. This is advantageous in that the need for providing a DCDC converter can be eliminated.

In the inverter system for driving a poly-phase motor as described above, a large number of auxiliary equipments,  
15 commonly in the form of vehicle accessories or auxiliary devices, are connected to the low voltage side battery, and the low voltage side battery therefore serves to supply constant electrical power to these devices. Namely, in the poly-phase motor driving inverter system, switching of the switching  
20 elements in the inverter is controlled to thereby control the neutral point voltage.

However, because the neutral point voltage cannot be continuously maintained at a constant value, when the low voltage battery is not available, the voltage to be supplied to  
25 the auxiliary equipment changes significantly and constant operation of the equipment is prohibited. Accordingly, when the low voltage side battery becomes disconnected (namely,

electrical connection is interrupted) in certain circumstances, the system suffers from the problem described above.

Further, in order to maintain the charging state of the low voltage side battery at a predetermined level, it is  
5 necessary to supply power in accordance with electrical power which is consumed by the auxiliary loads connected to the low voltage side battery to a power supply line to which the low voltage side battery is connected. Accordingly, conventionally, the voltage on the low voltage power supply  
10 line is sensed, and the electrical power generated by the motor is subjected to feedback control so as to maintain the sensed voltage constant.

However, the above conventional system suffers from a problem that generated power cannot be controlled in the event  
15 of that sensing of the voltage on the low voltage power supply line cannot be performed normally due to disconnection or the like, thereby causing overvoltage or low voltage.

Further, in the conventional system, a hall sensor is typically used as a position sensor and detects the position of  
20 a rotor only at 60 degree intervals. In order to obtain sufficient starting torque at the time of motor starting, 180 degree current flow type (current flows during 180 degree electrical angle and then polarity of the current is changed) is typically performed during startup of the motor. More  
25 specifically, as shown in Fig. 19, three phase rectangular wave voltage commands (indicated by a solid line, a dotted line, and

a chain and dot line in the uppermost view in Fig. 19) are used to generate rectangular wave switching control signals for the inverter (gate signals Su, Sv, Sw). Accordingly, the motor driving current is rectangular wave. When a motor is a three-  
5 phase motor, 180 degree conduction gate signals Su, Sv, and Sw with 120 degree phase shift are generated for driving the motor. Here, a period in which two phases are both ON or OFF occurs for a period which is 1/6 of the current cycle.

Further, for each phase current, by applying maximum current  
10 regulation which turns the corresponding phase off when the current value reaches a predetermined value, a period in which three phases are all ON or OFF occurs.

When the inverter retains the same switching state for a relatively long period and a difference between the neutral  
15 point potential and the low voltage target value is increased, the system suffers from a problem that the neutral point current changes significantly and the low voltage power supply line also changes significantly.

Japanese Patent Laid-Open Publication No. 2000-324857  
20 describes provision of a relay between a low voltage power supply and a neutral point so that the low voltage power supply line is separated from the neutral point by the relay during startup of the motor. With this configuration, although voltage change on the low voltage power supply line during  
25 startup can be reduced, it is necessary to additionally provide a relay and to switch the relay ON and OFF as required.

## DISCLOSURE OF THE INVENTION

The present invention advantageously provides an inverter  
5 system for driving a poly-phase motor, which is capable of  
reliably detecting disconnection of a low voltage battery.

The present invention further advantageously enables  
appropriate power generation control, even in the event of an  
abnormality in the measurement or detection of a low voltage  
10 side power supply line.

The present invention further advantageously effectively  
reduces significant changes in the neutral point current during  
startup.

According to one aspect of the present invention,  
15 abnormality is determined based on a detection result obtained  
from neutral point state detecting means of an alternating  
current motor.

Neutral point voltage or neutral point current is smoothed  
due to the presence of a power supply. When the power supply  
20 is disconnected, however, the neutral point current or neutral  
point voltage is likely to vary because no effect can be  
obtained from the power supply. It is therefore possible to  
effectively detect abnormality of power supply disconnection  
based on the state of the neutral point.

25 Further, according to another aspect of the present  
invention, when the voltage of a power supply connected to the

motor neutral point cannot be measured, the neutral point voltage of the inverter is controlled using power supply current. It is therefore possible to control the neutral point voltage of the inverter even when the voltage of the power supply connected to the motor neutral point cannot be measured.

Still further, according to another aspect of the present invention, ON/OFF of the switching elements of the inverter is controlled based on a gate signal obtained by comparison between a sinusoidal wave voltage command and carrier, so that the sinusoidal wave voltage command is limited to a predetermined range with respect to the carrier amplitude. Thus, a gate signal having the same frequency as the carrier frequency can be obtained. It is therefore possible to prevent a problem that switching pattern remains the same for a long period and significant current flows as neutral point current.

#### BRIEF DESCRIPTION OF THE DRAWINGS

These and other objects of the invention will be explained in the description below, in connection with the accompanying drawings, in which:

Fig. 1 is a view showing a configuration of a system according to a first embodiment of the present invention;

Fig. 2 is a view showing a waveform of a neutral point voltage;



Fig. 3 is a flowchart for explaining the operation of abnormality detection;

Fig. 4 is a view showing a configuration of another system according to the first embodiment of the present invention;

5 Fig. 5 is a view showing a waveform of a neutral point voltage;

Fig. 6 is a flowchart for explaining the operation of abnormality detection;

10 Fig. 7 is a view showing a configuration of a system according to a second embodiment of the present invention;

Fig. 8 is a flowchart for explaining the operation of the second embodiment;

Fig. 9 is a view showing a configuration of a control circuit of the embodiment shown in Fig. 7;

15 Fig. 10 is a view showing a configuration of another system according to the second embodiment of the present invention;

Fig. 11 is a view showing a configuration of a control circuit of the system shown in Fig. 10;

20 Fig. 12 is a view showing a configuration of another system according to the second embodiment of the present invention;

Fig. 13 is a view showing a configuration of a control circuit of the system shown in Fig. 12;

25 Fig. 14 is a view showing a configuration of a system according to a third embodiment of the present invention;

Fig. 15 is a view showing an operation of carrier comparison according to the embodiment shown in Fig. 14;

Fig. 16 is a view showing a configuration of a control circuit of the embodiment shown in Fig. 14;

5 Fig. 17 is a view showing a configuration of a system according to the third embodiment of the present invention;

Fig. 18 is a view showing a configuration of a control circuit of the system shown in Fig. 17; and

10 Fig. 19 is a view showing an example operation of convention carrier comparison.

#### DETAILED EXPLANATION OF PREFERRED EMBODIMENTS

Preferred embodiments of the present invention will be  
15 described with reference to the drawings.

##### Embodiment 1

Fig. 1 shows the overall configuration of an inverter system for driving a poly-phase motor in accordance with an  
20 embodiment of the present invention. An inverter 12 is connected to a 36-volt (42V when charged) battery 10 which serves as a main power supply. Namely, a voltage of 36V output from the battery 10 is applied between a positive bus and a negative bus of the inverter 12.

25 The inverter 12 has three arms provided in parallel each including two switching elements (transistors) arranged between the positive bus and the negative bus. The inter-transistor

points in the respective arms connect respectively to three phase motor output terminals.

Three phase motor coil terminals of a three-phase alternating current motor 14 are respectively connected to the  
5 three phase motor output terminals of the inverter 12. Accordingly, while one of the upper transistors of the inverter 12 is sequentially turned on, a transistor of other arms is sequentially turned on, so that a motor current with 120° phase difference is applied to each phase coil of the alternating  
10 current motor 14.

Further, to the neutral point of the alternating current motor 14, a positive electrode of an auxiliary battery 18 and various auxiliary loads 20 are connected via a reactor 16. A voltmeter 22 is connected between the auxiliary battery 18 and  
15 the reactor 16 for detecting voltage on a power supply line for the auxiliary battery 18. The output of the voltmeter 22 (battery voltage:  $V_{bs}$ ) is supplied to a control circuit 24.

The control circuit 24 determines the size of a ripple component from the output from the voltmeter 22, and detects  
20 abnormality such as disconnection of the auxiliary battery 18 when the ripple size is a predetermined level or greater.

In such a system, it is possible to control the neutral point voltage by changing an on duty ratio between the upper transistor and the lower transistor of the inverter 12. More  
25 specifically, when the ON periods are identical for both transistors, the neutral point voltage is equivalent to inverter input voltage (voltage of the battery 10). On the

other hand, when the ON period for the upper transistor is 2 with regard to the ON period 1 of the lower transistor, the neutral point voltage is one third of the voltage of the battery 10.

5        For example, when the voltage of the battery 10 is 36V (42V when charged), the voltage of the auxiliary battery 18 is 12V (14V when charged). Then, electrical power supplied from the battery 10 is used to drive the alternating current motor 14 for performing torque assist during startup of a vehicle, 10 for example, whereas electrical power from the auxiliary battery 18 is used to operate the various auxiliary loads 20.

      Here, because the neutral point voltage is controlled such that it is one third of the voltage of the battery 10, the 15 ON periods of the upper and lower transistors in the inverter 12 are unbalanced, causing the neutral point voltage to oscillate in accordance with the phase of the current supply to each motor phase. The reactor 16 smoothes the oscillating neutral point voltage to a certain extent, and the output 20 voltage of the reactor 16 is maintained at substantially constant level by the auxiliary battery 18.

      However, when the auxiliary battery 18 is disconnected for some reason, the output of the reactor 16 is used to supply voltage to the auxiliary power supply line. While the voltage 25 of the auxiliary power supply line remains substantially constant due to the capability of the auxiliary battery 18 when

the auxiliary battery 18 is connected, once the auxiliary battery 18 becomes disconnected, the affects of voltage changes in the neural point directly appear in the auxiliary battery line.

5       Namely, similar to the neutral point voltage, the auxiliary power supply line also changes in accordance with the peak of each phase current of the motor. More specifically, the voltage of the auxiliary power supply line changes in a cycle which is three times that of each phase current of the  
10 motor, as shown in Fig. 2.

According to the present embodiment, the control circuit 24 detects the size of the ripple component and determines abnormality when the detected value meets or exceeds a predetermined level. The determination operation performed by  
15 the control circuit 24 will be described with reference to Fig. 3.

It is first determined whether or not other abnormalities are found (S11). When no other abnormalities are found, it is then determined whether or not an absolute value of a value  
20 obtained by subtracting the target voltage (voltage command value)  $V_{bs}^*$  of the 14V system from the average voltage value  $V_{bsave}$  of the 14V system is less than a predetermined threshold value  $a$  (S12). If YES, it is then determined whether or not the ripple of the 14V power supply, namely the peak to peak  
25 voltage  $V_{bsp-p}$  of the alternating current component shown in Fig. 2 is greater than a predetermined threshold value  $b$  (S13).

When the determination at step S13 is YES, it is determined that the auxiliary battery is not operating normally (S14).

Here, the average voltage  $V_{bsave}$  of the 14V system auxiliary power supply line is approximately 13.5V to 14.5V, though it is variable depending on temperature. In accordance with the average voltage  $V_{bsave}$ , the target voltage  $V_{bs*}$  is determined to be 14V and the threshold value  $a$  is determined to be approximately 1V. Further, the threshold value  $b$  is set to approximately 0.5V, though it depends on reactance of the reactor 16..

When the determination at step S11 or S12 is NO, it is determined that determination is not possible (S16). When NO is determined at step S13, it is determined that the auxiliary battery is operating normally, that is, that there is no abnormality (S15).

Referring to Fig. 4, a configuration in accordance with another example is shown, in which an ammeter 28 is provided in place of the voltmeter 22. More specifically, the ammeter 28 is provided before the connection point at which the reactor 16 and the positive electrode of the auxiliary battery 18 are connected, for detecting current flowing between the neutral point and the auxiliary battery 18 and between the neutral point and the auxiliary load 20. The control circuit 24 determines abnormality in accordance with the detection result of the ammeter 28.

Specifically, as shown in Fig. 6, is it first determined whether or not other abnormalities are found (S21). When no other abnormalities are found, it is then determined whether or not the ripple of the neutral point current which is detected  
5 by the ammeter 28, namely the peak to peak current value  $I_{np-p}$  of the alternating current component shown in Fig. 5, is larger than a predetermined threshold  $c$  (S22). If YES, it is then determined that the auxiliary battery is operating abnormally (S23).

10 On the other hand, when the determination at step S21 is NO, it is determined that determination is not possible (S25). When the determination at step S22 is NO, it is determined that no abnormality is found (S24).

As described above, according to the system of the present  
15 embodiment, it is possible to effectively detect an abnormality of the auxiliary battery.

Further, this control operation may be preferably combined with a control operation of adjusting each phase output voltage command described above in accordance with the carrier  
20 amplitude.

Here, it is preferable that the alternating current motor  
14 is one used for a vehicle, and is mounted on a vehicle. The auxiliary load 20 may be any of various auxiliaries mounted on the vehicle. Further the alternating current motor 14 mounted  
25 on a vehicle may preferably be a motor generator for Eco Run System which is described in Japanese Patent Laid-Open Publication No. 2002-155773.

More specifically, this motor generator is used, for example, for (i) traveling of a vehicle with the engine automatically actuated in a case in which the vehicle is started after idling stop control is performed for shutting  
5 down the engine operation when the vehicle stops; (ii) regenerative power generation achieved by transmitting the revolution of a wheel via a drive system when the driving speed is reduced; (iii) driving of a compressor used for an air conditioner and a pump used for power steering at the time of  
10 engine stop due to stop of a vehicle; (iv) power generation when the engine is being driven; (v) control of the revolution of the engine which is not activated to reduce the vibration generated at the time of engine stop; and (vi) prevention of engine stalling as a result of reduced fuel supply to the  
15 engine during deceleration, until the engine is recovered and normal fuel supply resumed.

As described above, according to the present embodiment, abnormality is determined based on the state of current or voltage at the neutral point. Although the neutral point  
20 voltage or the neutral point current is smoothed by the presence of the power supply, it is likely to change when the power supply is disconnected and therefore does not influence the neutral point voltage and current. It is therefore possible to effectively detect abnormality that power supply is  
25 disconnected according to the state of the neutral point.

Further, the neutral point voltage and the neutral point current contains ripples based on the motor driving current.



By detecting the size of these ripples, it is possible to effectively detect disconnection of the power supply.

#### Embodiment 2

5        Fig. 7 shows a configuration of the system according to a second embodiment of the present invention. In this embodiment, in addition to the voltmeter 22, an ammeter 26 is provided between the auxiliary battery 18 and the power supply line for detecting current of the auxiliary battery 18 (battery  
10    current:  $I_{bs}$ ). The output from the ammeter 26 is also supplied to the control circuit 24.

      The control circuit 24 measures values related to abnormality, as shown in Fig. 8. Specifically, it is first determined whether or not there is an abnormality in voltage  
15    sensing of the power supply line (14V system power supply line) to which the auxiliary battery 18 is connected(S11). This is determined by determining whether or not the output  $V_{bs}$  of the voltmeter 22 has a normal value. For example, when the output voltage  $V_{bs}$  is 8V or less, the various auxiliary loads cannot  
20    be driven normally, and abnormality is determined. In particular, when the voltage  $V_{bs}$  is 0V, it is determined a certain failure has occurred.

      When the determination at step S11 is NO, it is determined there is no problem and switching of the inverter 12 is  
25    controlled based on the detected  $V_{bs}$  (14V system voltage).

When it is determined at step S11 that an abnormality exists, a warning indicative of the abnormality is issued (S13). For example, the display panel may indicate the sign "14V system battery sensing abnormal" or a lamp used for  
5 indicating abnormality of the auxiliary battery may be turned on.

Then, a value  $I_{bs}$  of the ammeter 26 is detected. Because the value  $I_{bs}$  represents a difference between current flowing through the auxiliary loads and the neutral point current, when  
10 the inverter 12 is controlled so as to make the value  $I_{bs}$  0, it is possible to match the power used by the auxiliary load with the power generated by the motor 14. Therefore, according to the present embodiment, the inverter 12 is controlled such that the current  $I_{bs}$  becomes 0.

15 When 14V system voltage sensing is abnormal, feedback control cannot be performed and the generated voltage significantly deviates from the target, making occurrence of overvoltage and voltage reduction very likely. In such a case, the auxiliary battery 18 become incapable of running due to  
20 overcharge or rapid discharge, and the auxiliary loads suffer from failure caused by overvoltage and operation defect due to voltage reduction, and need for resetting a CPU also occurs. According to this embodiment, these problems can be prevented by substantially maintaining power generated by the motor 14 to  
25 the correct level using feedback control based on the sensing of the current  $I_{bs}$ . Further, by issuance of abnormality

warnings, it is possible to appropriately resume the voltage sensing such that a normal state can be recovered before a serious problem occurs.

Fig. 9 shows a configuration of the control circuit 24.

5 The voltage  $V_{bm}$  of the high voltage battery 10 is measured and a difference between the voltage  $V_{bm}$  and the target voltage  $V_{bm}^*$  is supplied to a  $V_{bm}$  feedback (F/B) section 30. The  $V_{bm}$  feedback (F/B) section 30 determines a torque command  $T_{mg}^*$  of the motor 14 in such a manner that the voltage  $V_{bm}$  of the  
10 battery 10 corresponds to the target voltage  $V_{bm}^*$ , and supplies the determined torque command  $T_{mg}^*$  to a switching operation section 32. Here, the torque command  $T_{mg}^*$  corresponds to power generation command of the motor 14.

Each phase coil current  $I_u$ ,  $I_v$ ,  $I_w$  of the motor 14 and a  
15 detection signal  $\theta$  regarding the rotor position are also supplied to the switching operation section 32. The switching operation section 32 generates signals  $S_u$ ,  $S_v$ ,  $S_w$  for controlling switching of the switching elements of each phase of the inverter in accordance with these inputs to thereby  
20 control each phase current of the motor 14. Thus, the output torque (generated power) of the motor 14 is controlled so as to correspond to the torque command  $T_{mg}^*$ .

Further, a command value  $V_n$  of the neutral point voltage of the motor 14 is supplied to the switching operation section  
25 32. Thus, a ratio of ON periods between the upper and lower

switching elements of the inverter is controlled to control the neutral point voltage.

During normal operation, this neutral point voltage  $V_n$  is determined such that a difference between the voltage  $V_{bs}$  of the auxiliary battery 18 and the command value  $V_{bs}^*$  thereof is supplied via a switching section 34 to the feedback (F/B) section 36 to make  $V_{bs}$  correspond to  $V_{bs}^*$ . When an existence of an abnormality is determined at the above-described step S11 of Fig. 8, however, a switching signal is output at step S14, so that the switching section 34 supplies a difference between the auxiliary battery current  $I_{bs}$  and the command value thereof  $I_{bs}^*$  to the feedback (F/B) section 36. Consequently,  $V_n$  is generated in the feedback (F/B) section 36 based on the auxiliary battery current  $I_{bs}$ . Because the switching operation section 32 controls switching of the inverter 12 based on this  $V_n$ , the neutral point of the motor 14 is controlled to a voltage in accordance with the power consumption by the auxiliary loads.

The control of the neutral point voltage  $V_n$  and the voltage  $V_{bm}$  of the battery 10 will be briefly described.

In this system, it is possible to control the neutral point voltage by changing an on duty ratio between the upper transistor and the lower transistor of the inverter 12. More specifically, when the ON periods are identical for both transistors, the neutral point voltage is equivalent to inverter input voltage (voltage of the battery 10). On the

other hand, when the ON period for the upper transistor is 2 with regard to the ON period 1 of the lower transistor, the neutral point voltage is one third of the voltage of the battery 10.

5 For example, when the voltage of the battery 10 is 36V (42V when charged), the voltage of the auxiliary battery 18 is 12V (14V when charged). Then, electrical power supplied from the battery 10 is used to drive the alternating current motor 14 for performing torque assist during startup of a vehicle, 10 for example, whereas electrical power from the auxiliary battery 18 is used to operate the various auxiliary loads 20.

Here, because the neutral point voltage is controlled such that it is one third of the voltage of the battery 10, the ON periods of the upper and lower transistors in the inverter 12 15 are unbalanced, causing the neutral point voltage to oscillate in accordance with the phase of the current supply to each motor phase. The reactor 16 smoothes the oscillating neutral point voltage to a certain extent, and the output voltage of the reactor 16 is maintained at substantially constant level by 20 the auxiliary battery 18.

Fig. 10 shows a configuration of a system in accordance with another example of the present invention, in which ammeters 28u, 28v, 28w are adopted for each measuring current of each phase coil of the motor in place of the ammeter 26. 25 Here, because currents  $I_u$ ,  $I_v$ ,  $I_w$  of each phase coil of the motor 14 are necessary for calculating the torque command  $T_{mg}^*$

as described in Fig. 9, the ammeters 28u, 28v, 28w are originally provided. In this example, each phase coil current is utilized for control.

Here, in the absence of the neutral point current, the sum of each phase coil current should be 0. The sum of the currents  $I_u$ ,  $I_v$ ,  $I_w$  of the respective phases therefore corresponds to the neutral point current  $I_n$ . When the neutral point current  $I_n$  is controlled such that it corresponds to the current consumed by the whole auxiliary loads connected to the 14V power supply line, appropriate power is supplied to the 14V power supply. It is therefore possible to measure the current consumed by the auxiliary loads, determine the target value  $I_n^*$  of the neutral point current based on the consumed current, and then control the neutral point current  $I_n$  so as to correspond to the target value  $I_n^*$ .

However, it is generally impossible to measure the consumed current in all the auxiliary loads. Therefore, according to this example, the minimum consumed current of the whole auxiliary loads is previously obtained, and the target neutral point current  $I_n^*$  is set to the minimum consumed current.

In this manner, overcharging of the auxiliary battery 18 can be prevented. Although the auxiliary battery 18 discharges when the power consumption of the auxiliary loads increases, rapid discharge of the auxiliary battery 18 can still be prevented.

Fig. 11 shows a configuration of the control circuit 24 according to the present embodiment. As described above, at the time of abnormality, a difference between the neutral point current and the target value thereof ( $I_{n*} - I_n$ ) is selected in the switching section 34 and is supplied to the feedback (F/B) section 36. The feedback (F/B) section 36 then generates a neutral point voltage target value  $V_n$  based on the difference and supplies the target value  $V_n$  to the operation section 32.

As a more simple method, it is also possible to eliminate even the feedback of battery current or neutral point current and to calculate the neutral point voltage command  $V_n$  using open loop feed-forward control. For example, the neutral point voltage command  $V_n$  is set to 14V. With this system, although accuracy of voltage generation control is lowered, it is still possible to perform improved control compared to when no control is performed.

Fig. 12 shows a system configuration example in which control accuracy is enhanced in open loop control. In this example, during normal operation, a difference between the auxiliary load power supply line voltage command  $V_{bs*}$  and the the auxiliary load power supply line voltage  $V_{bs}$  is input to the control circuit 24 so as to correct the control of the inverter 12.

Fig. 13 shows a configuration of the control circuit 24 according to this embodiment.

Specifically, a difference between the auxiliary load power supply line voltage command  $V_{bs}^*$  and the voltage  $V_{bs}$  is input to the feedback (F/B) section 36, where a neutral point voltage command  $V_n$  is generated and is supplied via the  
5 switching section 34 to the switching operation section 32. In the event of an abnormality, on the other hand, values for the revolution of the motor  $N_{mg}$ , the motor output torque command  $T_{mg}^*$ , and the voltage  $V_{bm}$  of the battery 10 are input to the map 38 which outputs a corrected neutral point voltage command  
10  $V_n$ . The corrected output  $V_n$  is then supplied via the switching section 34 to the switching operation section 32.

It is thus possible to correct  $V_n$  based on the operation state or the like when abnormalities occur, so that driving of inverter can be controlled in a manner which suits the present  
15 situation.

Here, it is preferable that the alternating current motor 14 is one used for a vehicle, and is mounted on a vehicle. The auxiliary load 20 may be any of various auxiliaries mounted on the vehicle. Further the alternating current motor 14 mounted  
20 on a vehicle may preferably be a motor generator for Eco Run System which is described in Japanese Patent Laid-Open Publication No. 2002-155773.

More specifically, this motor generator is used, for example, for (i) traveling of a vehicle with the engine  
25 automatically actuated in a case in which the vehicle is started after idling stop control is performed for shutting down the engine operation when the vehicle stops; (ii)



regenerative power generation achieved by transmitting the revolution of a wheel via a drive system when the driving speed is reduced; (iii) driving of a compressor used for an air conditioner and a pump used for power steering at the time of engine stop due to stop of a vehicle; (iv) power generation when the engine is being driven; (v) control of the revolution of the engine which is not activated to reduce the vibration generated at the time of engine stop; and (vi) prevention of engine stalling as a result of reduced fuel supply to the engine during deceleration, until the engine is recovered and normal fuel supply resumed.

As described above, according to the present embodiment, when the voltage of the power supply connected to the motor neutral point cannot be measured, the feedback control can be continuously performed using power supply current.

Further, by controlling the neutral point current so as to correspond to the consumed current of the auxiliary loads, appropriate inverter control can be achieved.

Also, by setting the neutral point voltage to a voltage which is appropriate as a power supply voltage of the auxiliary loads, control can be continued in a simple manner.

### Embodiment 3

Referring to Fig. 14, a system configuration in accordance with a third embodiment is shown. In this embodiment, a resolver 28 is provided for detecting a rotation angle of the

motor and the output from the resolver 28 is supplied to the control circuit 24.

As described above, during normal operation, the control circuit 24 controls switching of the inverter 12 based on the output V<sub>bs</sub> of the voltmeter 22 to control the current to be supplied to the motor 14, thereby controlling power generation of the motor 14 such that the voltage V<sub>bs</sub> becomes a desired value (14V, for example).

Specifically, it is possible to control the neutral point voltage by changing an on duty ratio between the upper transistor and the lower transistor of the inverter 12. More specifically, when the ON periods are identical for both transistors, the neutral point voltage is equivalent to inverter input voltage (voltage of the battery 10). On the other hand, when the ON period for the upper transistor is 2 with regard to the ON period 1 of the lower transistor, the neutral point voltage is one third of the voltage of the battery 10.

For example, when the voltage of the battery 10 is 36V (42V when charged), the voltage of the auxiliary battery 18 is 12V (14V when charged). Then, electrical power supplied from the battery 10 is used to drive the alternating current motor 14 for performing torque assist during start up of a vehicle, for example, whereas electrical power from the auxiliary battery 18 is used to operate the various auxiliary loads 20.

According to the present embodiment, the resolver 28 is provided to detect the rotation angle of the motor 14. The resolver 28 is a highly accurate angular sensor which has a configuration similar to that of an alternating current motor and generates two sinusoidal waves with 90 degree phase difference at the secondary coils in accordance with the rotation angle of the primary coil. The output from the resolver 28 is supplied to the control circuit 24 and is used for control of each phase current of the motor 14. In particular, during startup, each phase voltage command value which is a sinusoidal wave is generated in accordance with the output of the resolver 28. Each phase voltage command value is set within a predetermined range which does not exceed or does not significantly exceed the carrier amplitude.

For example, as shown in Fig. 15, each phase voltage command value is set slightly smaller than the carrier amplitude. As a result, a gate signal having the same frequency as the carrier frequency can be obtained. It is therefore possible to prevent the problem that the switching does not occur for a long period and significant current flows as neutral point current.

Because the neutral point potential is an average value of the phase voltage command values, it is possible to control the neutral point voltage to a target value by setting the average value to the target neutral point voltage. Although in the example shown in Fig. 15 the neutral point voltage is one half

the inverter input voltage for convenience, the control operation is basically the same when the neutral point voltage is one third of the inverter input voltage. Specifically, appropriate control can be achieved by adjusting the amplitude of each phase voltage command so that a gate signal which turns on and off at the carrier frequency can be generated.

Fig. 16 shows a circuit provided within the control circuit 24 for generating a gate signal. A torque command  $T_{mg}^*$ , each phase current  $I_u$ ,  $I_v$ ,  $I_w$ , and a resolver position signal  $\theta$  are supplied to a voltage command operation section 30. The voltage command operation section 30 calculates each phase voltage command  $V_u$ ,  $V_v$ ,  $V_w$ , as shown in Fig. 15, with mutual phase shift of 120 degree and having an amplitude which equals to amplitude of a triangular wave carrier, and supplies each phase voltage command to the correction circuit 32.

To this correction circuit 32, the neutral point voltage command  $V_n^*$  and the voltage  $V_{bm}$  of the battery 10 are supplied. The neutral point voltage command  $V_n^*$  has been calculated by the feedback (F/B) section 34 from a difference between the power supply line voltage  $V_{bs}$  of the auxiliary battery 18 and the target voltage value  $V_{bs}^*$  thereof. The correction circuit 32 then matches the average value of the each phase voltage command  $V_u$ ,  $V_v$ ,  $V_w$  to the  $V_n^*$  based on  $V_n^*$  and  $V_{bm}$ , and also corrects the output torque  $T_{mg}^*$  so that the  $V_{bm}$  corresponds to the target value  $V_{bm}^*$ . Thus, corrected voltage commands of

each phase  $Vu'$ ,  $Vv'$ ,  $Vw'$  are output from the correction circuit 32 and then supplied to a carrier comparison circuit 36.

In the carrier comparison circuit 36, to which a triangular wave which is carrier is supplied, each phase voltage command  $Vu'$ ,  $Vv'$ ,  $VW'$  is compared with the carrier and the gate signals  $Su$ ,  $Sv$ ,  $Sw$  shown in Fig. 15 are output.

According to the present embodiment, the amplitude of the each phase voltage command is controlled within a predetermined value due to calculation in the voltage command operation section 30. Consequently, the gate signals  $Su$ ,  $Sv$ ,  $Sw$  repeat ON and OFF at the carrier frequencies, so that it is possible to prevent significant change in the neutral point voltage.

Fig. 17 shows a system configuration according to still another example, one in which an ammeter 28 is provided for measuring the neutral point current  $I_n$ . The control circuit 24 uses the neutral point current  $I_n$  to apply feed-forward control to the neutral point voltage command at the time of control mode switching.

In this system, the control modes of the motor 14 include a stop mode, a start mode, and a power generation mode. In the control transition state in which the control modes are switched, for example, from the stop mode to the start mode or from the power generation mode to the stop mode, the feedback control which controls the neutral point voltage to the target voltage does not follow, which causes the neutral point voltage to be transitionally shifted from the auxiliary power supply

line target voltage and simultaneously changes the neutral point current.

Fig. 18 shows a configuration of the control circuit 24 according to this embodiment. As shown, the configuration according to this embodiment comprises a Vn operation section 38, where the target voltage of the auxiliary power supply line Vbs\* and the neutral point current In are supplied and the neutral point voltage command Vn\* is calculated by  $Vn* = Vbs* + RI \times In$ , taking consideration of the voltage drop by the reactor.

Then, both Vn\* which is output from the Vn operation section 38 and Vn\* which is output from the feedback (F/B) section 34 are input to the switching section 40. The switching section 40 selects the output from the Vn operation section 38 during startup, and selects the output from the feedback (F/B) section 34 after startup, the selected Vn\* being supplied to the correction circuit 32.

In this manner, only In is subjected to feedback whereas Vbs\* is always a correct target value, so that neutral point voltage control which includes feed-forward element can be performed. It is therefore possible to prevent the neutral point voltage from changing significantly from Vbs\*, so that stable control can be performed in the control transition period.

The above control is effective not only when starting the power generation mode switched from the stop mode, but also when shifting from the power generation mode to the stop mode.

Further, this control operation may be preferably combined  
5 with a control operation of adjusting each phase output voltage command described above in accordance with the carrier amplitude.

Here, it is preferable that the alternating current motor 14 is one used for a vehicle, and is mounted on a vehicle. The  
10 auxiliary load 20 may be any of various auxiliaries mounted on the vehicle. Further the alternating current motor 14 mounted on a vehicle may preferably be a motor generator for Eco Run System which is described in Japanese Patent Laid-Open Publication No. 2002-155773.

15 More specifically, this motor generator is used, for example, for (i) traveling of a vehicle with the engine automatically actuated in a case in which the vehicle is started after idling stop control is performed for shutting down the engine operation when the vehicle stops; (ii)  
20 regenerative power generation achieved by transmitting the revolution of a wheel via a drive system when the driving speed is reduced; (iii) driving of a compressor used for an air conditioner and a pump used for power steering at the time of engine stop due to stop of a vehicle; (iv) power generation  
25 when the engine is being driven; (v) control of the revolution of the engine which is not activated to reduce the vibration generated at the time of engine stop; and (vi) prevention of

engine stalling as a result of reduced fuel supply to the engine during deceleration, until the engine is recovered and normal fuel supply resumed.

5       As described above, according to the present embodiment, by limiting the sinusoidal wave voltage command within a predetermined range with regard to the carrier amplitude, a gate signal having the same frequency as the carrier frequency can be obtained. It is therefore possible to prevent the  
10 problem that the switching does not occur for a long period and significant current flows as the neutral point current.

Further, in the mode transition state, a feed-forward element is included in the neutral point voltage command, so that delay of the neutral point voltage control can be  
15 prevented, thereby achieving stable control.



## C L A I M S

1. An inverter system for driving a poly-phase motor,  
the system comprising:

5 an alternating current motor which is driven by an  
inverter for outputting drive force or generating power;

a power supply connected to a neutral point of the  
alternating current motor; and

neutral point state detecting means for detecting a state  
10 of current or voltage at the neutral point,

wherein abnormality determination is performed based on  
the detection result of the neutral point state detecting  
means.

15 2. An inverter system according to claim 1, wherein  
the neutral point state detecting means detects ripples of  
voltage at the neutral point.

3. An inverter system according to claim 1 or 2, wherein  
20 an auxiliary electrical device that consumes electrical  
power is connected to the power supply, and

the neutral point state detecting means detects ripples of  
current supplied to the auxiliary electrical device.

25 4. An inverter system according to claim 2 or 3, wherein

abnormality is determined when the ripples detected by the neutral point state detecting means are equal to or greater than a predetermined value.

5           5.    An inverter system according to any one of claims 1 to 4, wherein

          a reactor is connected between the neutral point and the power supply, and

          the neutral point state detecting means detects a state of  
10   current or voltage on the side of the power supply with respect to the reactor.

          6.    An abnormality detecting method in an inverter system for driving a poly-phase motor comprising an alternating  
15   current motor which is driven by an inverter and generates power, and a power supply connected to a neutral point of the alternating current motor, wherein

          a state of current or voltage at the neutral point is detected, and abnormality determination is performed based on  
20   the detection result.

          7.    An abnormality detecting program in an inverter system for driving a poly-phase motor comprising an alternating current motor which is driven by an inverter and generates  
25   power, a power supply connected to a neutral point of the alternating current motor, and an abnormality detecting

apparatus for monitoring current or voltage of the neutral point, wherein

the abnormality detecting program causes the abnormality detecting apparatus to capture a state of current or voltage at the neutral point and perform abnormality determination based on the captured state.

8. An inverter system for driving a poly-phase motor, an abnormality detecting method for the poly-phase motor driving inverter system or an abnormality detecting program for the poly-phase motor driving inverter system according to any one of claims 1 to 7, wherein

the alternating current motor is an alternating current motor used for a vehicle.

15

9. An inverter system for driving a poly-phase motor comprising an alternating current motor which is driven by an inverter for outputting drive force and generating power and a power supply connected to a neutral point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying electrical power to a plurality of electrical devices, the inverter system comprising:

power supply line voltage detecting means for detecting voltage on a power supply line to which the power supply is connected; and

power supply current detecting means for detecting current of the power supply, wherein

during normal operation, the inverter is controlled in accordance with an output of the power supply line voltage  
5 detecting means, and

when it is determined that the power supply line voltage detecting means is operating abnormally, the inverter is controlled in accordance with an output of the power supply current detecting means.

10

10. An inverter system according to claim 9, wherein  
in the event of an abnormality in the power supply line voltage detecting means, control is performed such that the power supply current becomes 0 in accordance with the output of  
15 the power supply current detecting means.

11. An inverter system for driving a poly-phase motor comprising an alternating current motor which is driven by an inverter for outputting drive force and generating power and a  
20 power supply connected to a neutral point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying electrical power to a plurality of electrical devices, the inverter system comprising:

power supply line voltage detecting means for detecting voltage on a power supply line to which the power supply is connected; and

neutral point current detecting means for detecting  
5 neutral point current which is input and output with respect to the neutral point of the alternating current motor, wherein

during normal operation, the inverter is controlled in accordance with an output of the power supply line voltage detecting means, and

10 when the power supply line voltage detecting means is operating abnormally, the inverter is controlled in accordance with an output of the neutral point current detecting means.

12. An inverter system according to claim 11, wherein  
15 the neutral point current detecting means detects current of each of three phases of the alternating current motor, and detects the neutral point current based on the detected values.

13. An inverter system for driving a poly-phase motor  
20 comprising an alternating current motor which is driven by an inverter for outputting drive force and generating power and a power supply connected to a neutral point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying  
25 electrical power to a plurality of electrical devices, the inverter system comprising:

power supply line voltage detecting means for detecting voltage on a power supply line to which the power supply is connected, and wherein

during normal operation, the inverter is controlled in  
5 accordance with an output of the power supply line voltage detecting means, and

when the power supply line voltage detecting means is operating abnormally, the inverter is controlled in accordance with a neutral point voltage command corresponding to a target  
10 voltage of the power supply.

14. An inverter system according to claim 13, wherein the neutral point voltage command is corrected base on at least one of revolution of the alternating current motor, an  
15 output torque command, and inverter input side voltage.

15. A control method of an inverter system for driving a poly-phase motor comprising an alternating current motor which is driven by an inverter for outputting drive force and  
20 generating power and a power supply connected to a neutral point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying electrical power to a plurality of electrical devices, wherein

during normal operation, the inverter is controlled in accordance with voltage of a power supply line to which the power supply is connected, and

in the event of abnormality in sensing of the power  
5 supply line voltage, the inverter is controlled in accordance with current of the power supply.

16. A control method of an inverter system for driving a poly-phase motor comprising an alternating current motor which  
10 is driven by an inverter for outputting drive force and generating power and a power supply connected to a neutral point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying electrical power to a plurality of electrical  
15 devices, wherein

during normal operation, the inverter is controlled in accordance with voltage of a power supply line to which the power supply is connected, and

in the event of abnormality in sensing of the power supply  
20 line voltage, the inverter is controlled in accordance with current of the neutral point.

17. A control method of an inverter system for driving a poly-phase motor comprising an alternating current motor which  
25 is driven by an inverter for outputting drive force and generating power and a power supply connected to a neutral

point of the alternating current motor, the power supply being charged by power generated by the alternating current motor and supplying electrical power to a plurality of electrical devices, wherein

5           during normal operation, the inverter is controlled in accordance with voltage of the power supply line, and

          in the event of abnormality in sensing of the power supply line voltage, the inverter is controlled in accordance with a neutral point voltage command corresponding to a target voltage  
10   of the power supply.

18. A control program of an inverter system for driving a poly-phase motor, the control program causing a system to perform a control method of a poly-phase motor driving inverter  
15   system according to any one of claims 15 to 17.

19. An inverter system for driving a poly-phase motor, an abnormality detecting method for the poly-phase motor driving inverter system or an abnormality detecting program for the  
20   poly-phase motor driving inverter system according to any one of claims 9 to 18, wherein

          the alternating current motor is an alternating current motor used for a vehicle.

25           20. An inverter system for driving a poly-phase motor, comprising a high voltage power supply, an inverter with the



high voltage power supply being connected to an input side and with an alternating current motor being connected to an output side, and a low voltage power supply connected to a neutral point of the alternating current motor, the inverter system  
5 controlling driving of the alternating current motor and transfer of electrical power between the high voltage power supply and the low voltage power supply by controlling driving of the inverter, wherein

switching of the inverter is performed by controlling the  
10 switching on and off of a switching element of the inverter based on a gate signal obtained from comparison between a voltage command which is sinusoidal wave and carrier, and

the voltage command which is sinusoidal wave is limited within a predetermined range with regard to the carrier  
15 amplitude.

21. An inverter system for driving a poly-phase motor comprising a high voltage power supply, an inverter with the high voltage power supply being connected to an input side and  
20 with an alternating current motor being connected to an output side, and a low voltage power supply connected to a neutral point of the alternating current motor, the inverter system controlling driving of the alternating current motor and transfer of electrical power between the high voltage power  
25 supply and the low voltage power supply by controlling driving of the inverter, wherein

driving control of the alternating current motor includes at least a stop mode and a power generation mode, and

a feed-forward element is included in a neutral point voltage command in a transition state of these modes.

5

22. A control method of an inverter system for driving a poly-phase motor comprising a high voltage power supply, an inverter having the high voltage power supply connected to an input side and having an alternating current motor connected to an output side, and a low voltage power supply connected to a neutral point of the alternating current motor, in which driving of the alternating current motor and transfer of electrical power between the high voltage power supply and the low voltage power supply is controlled by controlling driving of the inverter, wherein

switching of the inverter is performed by controlling on and off of switching element of the inverter based on a gate signal obtained from comparison between a voltage command which is sinusoidal wave and carrier, and

the voltage command which is sinusoidal wave is limited within a predetermined range with regard to the carrier amplitude.

23. A control method of an inverter system for driving a poly-phase motor comprising a high voltage power supply, an inverter with the high voltage power supply being connected to

an input side and with an alternating current motor being connected to an output side, and a low voltage power supply connected to a neutral point of the alternating current motor, in which driving of the alternating current motor and transfer  
5 of electrical power between the high voltage power supply and the low voltage power supply is controlled by controlling driving of the inverter, wherein

driving control of the alternating current motor includes at least a stop mode and a power generation mode, and

10 a feed-forward element is included in a neutral point voltage command in a transition state of these modes.

24. An inverter system for driving a poly-phase motor or a control method of an inverter system for driving a poly-phase  
15 motor according to any one of claims 20 to 23, wherein

the alternating current motor is an alternating current motor for a vehicle.




FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5






FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13






FIG. 14




FIG. 15




FIG. 16




FIG. 17




FIG. 18




FIG. 19

## INTERNATIONAL SEARCH REPORT

International Application No

PCT/JP 03/08363

## A. CLASSIFICATION OF SUBJECT MATTER

IPC 7 H02J7/00 H02P7/628 B60L11/00

According to International Patent Classification (IPC) or to both national classification and IPC

## B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

IPC 7 H02J H02P B60L

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

Electronic data base consulted during the international search (name of data base and, where practical, search terms used)

EPO-Internal, WPI Data, PAJ

## C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 1 034 968 A (TOYOTA MOTOR CO LTD) 13 September 2000 (2000-09-13) cited in the application paragraphs '0035!', '0039! figure 2 -----	1,6

☐ Further documents are listed in the continuation of box C.

Patent family members are listed in annex.

## \* Special categories of cited documents :

\*A\* document defining the general state of the art which is not considered to be of particular relevance

\*E\* earlier document but published on or after the international filing date

\*L\* document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)

\*O\* document referring to an oral disclosure, use, exhibition or other means

\*P\* document published prior to the international filing date but later than the priority date claimed

\*T\* later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention

\*X\* document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone

\*Y\* document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art.

\*&amp;\* document member of the same patent family

Date of the actual completion of the international search

7 November 2003

Date of mailing of the international search report

25/11/2003

Name and mailing address of the ISA

European Patent Office, P.B. 5818 Patentlaan 2  
NL - 2280 HV Rijswijk  
Tel. (+31-70) 340-2040, Tx. 31 651 epo nl,  
Fax: (+31-70) 340-3016

Authorized officer

Foussier, P

# INTERNATIONAL SEARCH REPORT

International application No.  
PCT/JP 03/08363

## Box I Observations where certain claims were found unsearchable (Continuation of item 1 of first sheet)

This International Search Report has not been established in respect of certain claims under Article 17(2)(a) for the following reasons:

1. ☐ Claims Nos.:  
because they relate to subject matter not required to be searched by this Authority, namely:
2. ☒ Claims Nos.: 7-24  
because they relate to parts of the International Application that do not comply with the prescribed requirements to such an extent that no meaningful International Search can be carried out, specifically:  
see FURTHER INFORMATION sheet PCT/ISA/210
3. ☐ Claims Nos.:  
because they are dependent claims and are not drafted in accordance with the second and third sentences of Rule 6.4(a).

## Box II Observations where unity of invention is lacking (Continuation of item 2 of first sheet)

This International Searching Authority found multiple inventions in this international application, as follows:

1. ☐ As all required additional search fees were timely paid by the applicant, this International Search Report covers all searchable claims.
2. ☐ As all searchable claims could be searched without effort justifying an additional fee, this Authority did not invite payment of any additional fee.
3. ☐ As only some of the required additional search fees were timely paid by the applicant, this International Search Report covers only those claims for which fees were paid, specifically claims Nos.:
4. ☐ No required additional search fees were timely paid by the applicant. Consequently, this International Search Report is restricted to the invention first mentioned in the claims; it is covered by claims Nos.:

### Remark on Protest

- ☐ The additional search fees were accompanied by the applicant's protest.
- ☐ No protest accompanied the payment of additional search fees.



## FURTHER INFORMATION CONTINUED FROM PCT/ISA/ 210

Continuation of Box I.2

Claims Nos.: 7-24

In view of the large number and also the wording of the independent claims presently on file, which render it difficult, if not impossible, to determine the matter for which protection is sought, the present application fails to comply with the clarity and conciseness requirements of Article 6 PCT (see also Rule 6.1(a) PCT) to such an extent that a meaningful search is impossible. Consequently, the search has been carried out for those parts of the application which do appear to be clear (and concise), namely claims 1 to 6.

The applicant's attention is drawn to the fact that claims, or parts of claims, relating to inventions in respect of which no international search report has been established need not be the subject of an international preliminary examination (Rule 66.1(e) PCT). The applicant is advised that the EPO policy when acting as an International Preliminary Examining Authority is normally not to carry out a preliminary examination on matter which has not been searched. This is the case irrespective of whether or not the claims are amended following receipt of the search report or during any Chapter II procedure.

# INTERNATIONAL SEARCH REPORT

Information on patent family members

International Application No

PCT/JP03/08363

Patent document cited in search report		Publication date	Patent family member(s)	Publication date
EP 1034968	A	13-09-2000	JP 2000324857 A	24-11-2000
			DE 60000294 D1	05-09-2002
			DE 60000294 T2	27-03-2003
			EP 1034968 A1	13-09-2000
			US 6476571 B1	05-11-2002

---